

# Firmware Update ~ AT-UHD-PRO3-66M

The PRO3 matrices can be updated through webGUI only.


Needed items:

- New firmware - Downloaded from either atlona.com or through a box.com link sent by a Technical Support representative
- IP address of the Matrix
- Computer on the same network as the Matrix
- Username and password to access the webGUI of the Matrix

## Updating

- Plug a LAN cable into the matrix and your network router (if not already connected to the network)
- Type the IP address of the matrix into a web browser (as seen below)

**Note:** Computer must be on the same network as the Matrix to access through IP



**Important:** If any stability issues are experienced, disable any anti-virus or firewall that may be interfering with network communication to the Matrix. Once set up is done and the matrix GUI is no longer being used, the firewall and anti-virus can be re-enabled.



### Admin Login


User name	<input type="text" value="root"/>
Password	<input type="password" value="....."/>
<input type="button" value="Login"/> <input type="button" value="clear"/>	

A login screen will appear (this is the same log in for admin and general users).

- Login using the username and password (this would have been set up during installation)

Once logged in:

- Select the link named 'Firmware' on the left side menu



Technical Support: US: 1 (877) 536-3976 International: 1 (408) 962-0515 AT-UHD-PRO3-66M

**Home**

- [Status](#)
- [Firmware](#)

**Settings**

- [Network](#)
- [Control](#)
- [Users](#)

**Configuration**

- [I/O](#)
- [Route Memory](#)
- [EDID](#)
- [HDCP](#)
- [Audio](#)
- [Logout](#)

**Firmware Status**

Matrix	
UI Firmware	1.4.28
HDMI	1.4.25
FPGA	0.3
HDBaseT TX VS100	13090C10
HDBaseT TX VS10	23090C10

HDBaseT Receivers	
Out 1: Output_1	No Link
Out 2: Output_2	No Link
Out 3: Output_3	No Link
Out 4: Output_4	No Link
Out 5: Output_5	No Link
Out 7: Output_7	No Link

Check for the most recent [firmware update!](#)

**Firmware Update**

Matrix

File

HDBaseT Receiver

The firmware page displays the matrix, HDBaseT transmitter chips, and HDBaseT receivers firmware versions to make it easier to see what needs to be updated.

- Select the browse button under Matrix in the Firmware Update section
- Select the new firmware file that was downloaded either from [atlona.com](http://atlona.com) or [box.com](http://box.com)
- Press the update button

A progress bar will display as the update is completed. After the update is complete, if a restart is required, the WebGUI will display a prompt. The firmware update is now complete.

The unit will need to be factory reset after the firmware upgrade. Use the RS-232 or IP command of "Mreset" to factory reset the unit. The matrix is ready to use after the reset finishes.

**Note:** Clear browser cookies after updating, this will ensure that the backup feature will work properly