

Update Instructions

The AT-UHD-HDVS-300-KIT can only be updated through the webGUI.

Needed items (webGUI):

- New firmware - Downloaded from atlona.com
- IP address of the AT-UHD-HDVS-300-KIT
- Computer on the same network as the AT-UHD-HDVS-300-KIT
- Username and password to access the webGUI

 **IMPORTANT:** Do not change the firmware file name, doing so may result in damage to the unit.

 **IMPORTANT:** You must use only Mozilla Firefox or Internet Explorer when upgrading the firmware, due to incompatibilities with other browsers i.e. Google Chrome.

Updating

1. Verify that an Ethernet cable is connected between the AT-UHD-HDVS-300-KIT and the network.
2. Type the IP address of the AT-UHD-HDVS-300-KIT into a web browser, as shown in the example below.

 **NOTE:** Computer must be on the same network as the AT-UHD-HDVS-300-KIT to access through IP.



 **IMPORTANT:** If any stability issues are experienced, disable any anti-virus or firewall that may be interfering with network communication to the AT-UHD-HDVS-300-KIT. Once set up is done and the webGUI is no longer being used, the firewall and anti-virus can be re-enabled. For assistance, refer to the Support section on www.atlona.com and search for article KB01141.



3. The login screen will be displayed. Login using the username and password. The default login credentials are:


Username: root

Password: Atlona

 **IMPORTANT:** Before updating the firmware, perform steps 4 - 6 to save the system settings to a file.

4. Click **Status** on the left side of the screen.

- Click the **Save System Settings** button.



ATLONA
 Technical Support US: 1 (877) 536-3976 International: 1 (408) 962-0515

AT-UHD-HDVS-300

Home

- Status
- Firmware

Settings

- Network
- Control
- Users

Configuration

- EDID
- Settings
- Setup
- Command

- Logout

System Information [Download Log](#)


Model	AT-UHD-HDVS-300
On-Time (h.m.s)	21:55:20
Firmware Version TX	1.0.15
Firmware Version RX	1.0.15
HDBaseT Firmware TX	7.1.11
HDBaseT Firmware RX	7.1.11
System name	AT-UHD-HDVS-300-xxxxx
MAC Address	B8:9E:80:03:41:09
Serial Number	xxxxxx

Video Information

Active input	
Signal Type	
Aspect	
Scan Mode	
Color Depth	

[Save System](#)

- The **Save As** dialog box will be displayed. Select the folder where the file will be saved. Click the **Save** button to save the file.
- Click **Firmware**, on the left side of the screen.



ATLONA
 Technical Support US: 1 (877) 536-3976 International: 1 (408) 962-0515

AT-UHD-HDVS-300

Home

- Status
- Firmware

Settings

- Network
- Control
- Users

Configuration

- EDID
- Settings
- Setup
- Command

- Logout

Firmware Status

Switcher

Firmware Version TX	1.0.15
Firmware Version RX	1.0.15
HDBaseT Firmware TX	7.1.11
HDBaseT Firmware RX	7.1.11

Firmware Update

File No file chosen

- Click the **Choose File** button, to select the firmware file.
- Click the **Update** button. A progress bar will be displayed during the update process.
- Once the update has been completed, re-login to the webGUI.