



# Three-Input HD Video Scaler for HDMI and VGA Signals

---

Application Programming Interface

AT-HD-SC-500

Atlona Manuals  
**Switchers**

## Version Information

---

Version	Release Date	Notes
1	03/19	Initial release

## Commands

The following tables provide an alphabetical list of commands available on the AT-HD-SC-500. All commands are case-sensitive and must be entered as documented. If the command fails or is entered incorrectly, then the feedback is “Command FAILED”.



**IMPORTANT:** Each command must be terminated with a carriage-return (0x0d) and the feedback is terminated with a carriage-return and line-feed (0x0a). In addition, when sending multiple commands, at least 500 milliseconds should be specified between each command.

Command	Description
AnaGain	Sets the gain of the analog audio input
ASPBGRND	Sets the matte color for the bars used in viewing letterbox formats
Aspect	Sets the aspect ratio of the output signal
ASwOutTime	Sets period of time after loss of signal before auto switching to the selected fallback input
ASwPrePort	Sets the default fallback input for auto-switching
AudioSrc	Set audio source for the HDMI inputs
AutoDispOff	Enables / disables display auto-off
AutoDispOn	Enables / disables display auto-on
AutoPwrMode	Set the display mode for auto power on and off
AutoSW	Enable/Disable auto switching or display auto switching status
Bass	Increases / decreases the amount of bass on the output
Broadcast	Enables / disables broadcast mode
BRT	Sets the picture brightness
BTNVol	Defines the behavior of the VOL+, VOL-, and MUTE buttons
CliIPAddr	Sets the IP address of the Telnet client
CliMode	Sets the login mode of the Telnet client
CliPass	Sets the password for the Telnet client
CliPort	Sets the listening port for the Telnet client
CliUser	Sets the username for the Telnet client
CMDFMT	Sets the display format for commands
CSpara	Sets the baud rate, data bits, stop bits, and parity for the serial device
CtlType	Sets the communication protocol used to send the on/off command
CTRST	Sets the picture contrast
DisWarmUp	Sets the Display power-on time interval when locking the DISPLAY button
DispBtn	Simulates pressing the DISPLAY button on the front panel
Down	Scrolls the cursor down on position in the OSD
HDCPSet1	Sets the HDCP reporting mode for HDMI IN 1
HDCPSet2	Sets the HDCP reporting mode for HDMI IN 2
HDMIAUD	Enables / disables audio on the HDMI output

Command	Description
Help	Displays the list of available commands
HUE	Sets the picture hue
HZoom	Sets the horizontal zoom (overscan) for the output image
INFOOSD	Enables / disables the OSD info screen
INFOTMR	Sets the time interval for the info screen before it is hidden
Input	Sets the active input
IPAddUser	Adds a user for Telnet control
IPCFG	Displays the current network settings for the AT-HD-SC-500
IPDelUser	Deletes the specified Telnet user
IPDHCP	Enables / disables DHCP mode on the AT-HD-SC-500
IPLogin	Enables / disables login credentials when starting a Telnet session
IPPort	Sets the Telnet listening port for the AT-HD-SC-500
IPQuit	Terminates the Telnet session
IPStatic	Sets the static IP address, subnet mask, and gateway for the AT-HD-SC-500
IPTimeout	Specifies the time interval of inactivity before the Telnet session is closed
LampCool	Sets the cool-down interval before the projector can be powered-off
Lock	Locks the buttons on the front panel
LRAUD	Enables / disables the L/R audio output
MENUTMR	Specifies the time interval of inactivity before the OSD menu is hidden
MirrorV	Vertically mirrors the video
Mreset	Resets the AT-HD-SC-500 to factory-default settings
OSD	Sets the location of the OSD menu on the screen
OSDAIpha	Sets the transparency of the OSD menu
OSDBGRND	Sets the background color of the OSD menu
PicReset	Resets all picture settings
PTIMGHDMI	Sets the preferred HDMI input timing
PTIMGVGA	Sets the preferred VGA input timing
PWLock	Locks / unlocks the DISPLAY key on the front panel
QOSD	Exits the OSD menu
RAtIMac	Displays the MAC address of the AT-HD-SC-500
SATRT	Sets the picture color saturation
Select	Confirms the selection in the OSD
SetCmd	Assigns an RS-232 or IP command to the specified button on the front panel
SetCmdFB	Sets the feedback string for the specified command key
SetCS	Sets the output color space

Command	Description
SetEnd	Sets the end-character of the specified command
SetOff	Sets the time period to place the unit in standby
SHARP	Sets the picture sharpness
System	Displays system information about the AT-HD-SC-500
Treble	Increases / decreases the treble on the output
TrigCEC	Triggers the stored CEC command
TrigIP	Triggers the stored IP commands to the Telnet client
TrigRS	Triggers the stored command from RS-232 or IP
UARTPara	Sets the baud rate, data bits, parity, and stop bits for the serial port
Unlock	Unlocks the buttons on the front panel
Up	Scrolls up the cursor, in the OSD menu, one position
Version	Displays the current firmware version of the AT-HD-SC-500
VGAAuto	Automatically adjusts the clock and phase of the VGA signal
VidOutRes	Sets the video output resolution
VOUT1	Increases / decreases the audio volume
VOUTMute1	Mutes / unmutes the audio
VOUTOSD	Enables / disables the volume bar in the OSD
VZoom	Adjusts the vertical zoom (overscan) of the output image
x1\$	Enables / disables the HDMI video output
Zoom	Enables / disables overscan

### AnaGain

Sets the gain of the analog input.

#### Syntax

```
AnaGain X
```

Parameter	Description	Range
X	Audio gain	0 ... 16

**Example**  
AnaGain 1

**Feedback**  
AnaGain 1

### ASPBGRND

Sets the matte color when viewing an image that has been processed in “letterbox” format. The default setting is grey.

#### Syntax

```
ASPBGRND X
```

Parameter	Description	Range
X	Matte color	0 = Grey 1 = Black

**Example**  
ASPBGRND 1

**Feedback**  
ASPBGRND 1

### Aspect

Sets the aspect ratio of the output signal. The default setting is **Full**.

#### Syntax

```
Aspect X
```

Parameter	Description	Range
X	Aspect ratio	0 = Full 1 = 16:9 2 = 16:10 3 = 4:3 4 = Keep Ratio

**Example**  
Aspect 1

**Feedback**  
Aspect 1

### ASwOutTime

Sets the time interval after loss of signal occurs, before automatically switching to the selected fallback input. Execute the **ASwPrePort** command to set the fallback input.

#### Syntax

```
ASwOutTime X
```

Parameter	Description	Range
X	Time (in seconds)	1 ... 600

#### Example

```
ASwOutTime 15
```

#### Feedback

```
ASwOutTime 15
```

### ASwPrePort

Sets the fallback input when auto-switching is enabled. Use the **sta** argument to return the current fallback input. To always return the AT-HD-SC-500 to the last active input, use the **Prev** argument.

#### Syntax

```
ASwPrePort X
```

Parameter	Description	Range
X	Port	HDMI1, HDMI2, VGA, Prev, sta

#### Example

```
ASwPrePort HDMI1
```

#### Feedback

```
ASwPrePort HDMI1
```

### AudioSrc

Sets the audio source for the each HDMI input. Parameter X specifies the HDMI port. Parameter Y specifies the type of audio that will be used.

#### Syntax

```
AudioSrcX Y
```

Parameter	Description	Range
X	Port	HDMI1, HDMI2, VGA, Prev, sta
Y	Audio type	auto = Automatically selects the audio type dig = Digital audio only ana = Analog audio from the AUDIO IN port is embedded on the output.

#### Example

```
AudioSrc1 ana
```

#### Feedback

```
AudioSrc1 ana
```

### AutoDispOff

Sends the command to power-off the display when an A/V signal is no longer present. Use the **on** argument to enable this feature. Use the **sta** argument to return the current **AutoDispOff** setting.

#### Syntax

```
AutoDispOff X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

```
AutoDispOff on
```

#### Feedback

```
AutoDispOff on
```

### AutoDispOn

Sends the command to power-on the display when an A/V signal is detected. Use the **on** argument to enable this feature. Use the **sta** argument to return the current **AutoDispOff** setting.

#### Syntax

```
AutoDispOn X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

```
AutoDispOn on
```

#### Feedback

```
AutoDispOn on
```

### AutoPwrMode

Sets the display mode for auto-power on and off.

#### Syntax

```
AutoPwrMode X
```

Parameter	Description	Range
X	Value	DISPAVON, DISPAVSW, AVSW, sta

#### Example

```
AutoPwrMode DISPAVON
```

#### Feedback

```
AutoPwrMode DISPAVON
```



### AutoSW

Enables / disables auto switching or display auto switching status.

#### Syntax

```
AutoSW X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

AutoSW on

#### Feedback

AutoSW on

### Bass

Increases / decreases the amount of bass on the **output**. In addition to specifying an integer value, the + and - arguments can be used, by themselves, to increase or decrease the bass by 1 value, respectively.

#### Syntax

```
Bass X
```

Parameter	Description	Range
X	Value	-12 ... 15, sta

#### Example

Bass -5

Bass +

#### Feedback

Bass -5

Bass -4

### Broadcast

Enables / disables broadcast mode. By default, broadcast mode is set to off. When set to on, changes in the web GUI will also be affected on the control system (if connected), via TCP/IP. To separate control between web GUI and Telnet, set this feature off. on = enables broadcast mode; off = disables broadcast mode; sta = displays the current Broadcast setting.

#### Syntax

```
Broadcast X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

Broadcast on

#### Feedback

Broadcast on

## BRT

Sets the picture brightness. Use the sta argument to display the current brightness setting.

### Syntax

```
BRT X
```

Parameter	Description	Range
X	Value	0 ... 100, sta

### Example

```
BRT 60
```

### Feedback

```
BRT 60
```

## BTNVol

Defines the behavior of the VOL+, VOL-, and MUTE buttons, on the front panel. AudOut = buttons will control volume level of the output, RS232 = buttons will send the commands using RS-232 to compatible extenders and displays, IP = buttons will send the commands over Ethernet using the LAN connection, sta = displays the current BTNVol setting.

### Syntax

```
BTNVol X
```

Parameter	Description	Range
X	Value	AudOut, RS232, IP, sta

### Example

```
BTNVol RS232
```

### Feedback

```
BTNVol RS232
```

## CliIPAddr

Sets the IP address of the Telnet client. The IP address must be specified in dot-decimal notation. Use the sta argument to display the IP address of the Telnet client. DHCP must be disabled before using this command. Refer to the [IPDHCP](#) command for more information.

### Syntax

```
CliIPAddr X
```

Parameter	Description	Range
X	IP address	0 ... 255 (per byte)

### Example

```
CliIPAddr 192.168.1.61
```

### Feedback

```
CliIPAddr 192.168.1.61
```

### CliMode

Sets the login mode of the Telnet client. login = requires login credentials, non-login = no login credentials required, sta = displays the current CliMode setting.

#### Syntax

```
CliMode X
```

Parameter	Description	Range
X	Value	login, non-login, sta

#### Example

```
CliMode login
```

#### Feedback

```
CliMode login
```

### CliPass

Sets the password for the Telnet client. Execute the CliPass command without arguments to display the current password. The default password is Atlona.

#### Syntax

```
CliPass X
```

Parameter	Description	Range
X	Password	20 characters (max)

#### Example

```
CliPass R3ind33r
```

#### Feedback

```
CliPass R3ind33r
```

### CliPort

Sets the listening port for the Telnet client. Use the sta argument to display the current listening port. The default port is 23.

#### Syntax

```
CliPort X
```

Parameter	Description	Range
X	Port	0 ... 65535

#### Example

```
CliPort 30
```

#### Feedback

```
CliPort 30
```

### CliUser

Sets the username for the Telnet client. Execute the CliUser command without arguments to display the current username.

#### Syntax

```
CliUser X
```

Parameter	Description	Range
X	Username	20 characters (max)

#### Example

```
CliUser BigBoss
```

#### Feedback

```
CliUser BigBoss
```

### CMDFMT

Sets the display format for commands. ascii = ASCII format, hex = hexadecimal format, sta = displays the current command format.

#### Syntax

```
CMDFMT X
```

Parameter	Description	Range
X	Format	ascii, hex, sta

#### Example

```
CMDFMT ascii
```

#### Feedback

```
CMDFMT ascii
```

### CSpa

Sets the baud rate, data bits, parity bit, and stop bits for the serial device. Use the sta argument to display the current serial port settings. Each argument must be separated by a comma; no spaces are permitted. Brackets must be used when executing this command.

#### Syntax

```
CSpa[W,X,Y,Z]
```

Parameter	Description	Range
W	Baud rate	2400, 4800, 9600, 19200, 38400, 57600, 115200
X	Data bits	7, 8
Y	Parity bit	None, Odd, Even
Z	Stop bits	1, 2

#### Example

```
CSpa[115200,8,0,1]  
CSpa[sta]
```

#### Feedback

```
CSpa[115200,8,0,1]  
CSpa [115200,8,0,1]
```

### CtrlType

Sets the communication protocol used to send the on/off command. rs232 = command set over rs232, IP = command sent over IP, CEC = command sent using CEC, sta = displays the current CtrlType setting.

#### Syntax

```
CtrlType X
```

Parameter	Description	Range
X	Protocol	rs232, IP, CEC, sta

**Example**  
CtrlType IP

**Feedback**  
CtrlType IP

### CTRST

Sets the picture contrast. Use the sta argument to display the current contrast setting.

#### Syntax

```
CTRST X
```

Parameter	Description	Range
X	Contrast	0 ... 100, sta

**Example**  
CTRST 65

**Feedback**  
CTRST 65

### DisWarmUp

Sets the time interval, in seconds, between when the display is powered on and when the **DISPLAY** button, on the front panel, will be locked. Use the sta argument to display the current time interval.

#### Syntax

```
DisWarmUp X
```

Parameter	Description	Range
X	Time interval	0 ... 300, sta

**Example**  
DisWarmUp 120

**Feedback**  
DisWarmUp 120

## DispBtn

Simulates pressing the **DISPLAY** button on the front panel, activating the display mode and RS-232/CEC/IP display control commands. On = simulates pressing the DISPLAY button to the “on” state, Off = simulates pressing the DISPLAY button to the “off” state, Tog = reverses the current state of the DISPLAY button, Sta = displays the current DispBtn setting.

### Syntax

DispBtn X

Parameter	Description	Range
X	Setting	On, Off, Tog, Sta

**Example**  
DispBtn on

**Feedback**  
DispBtn on

## Down

Scrolls down the cursor, in the OSD menu, one position.

### Syntax

Down

**This command does not require any parameters**

**Example**  
Down

**Feedback**  
Down

## HDCPSet1

Set the HDCP reporting mode of the **HDMI IN 1** port. Some computers will send HDCP content if an HDCP-compliant display is detected. Setting this value to off, will force the computer to ignore detection of HDCP-compliant displays. Disabling this feature will *not* decrypt HDCP content. on = enables HDCP detection; off = disables HDCP detection; sta = displays the current HDCPSet1 setting.

### Syntax

HDCPSet1 X

Parameter	Description	Range
X	Value	on, off, sta

**Example**  
HDCPSet1 on

**Feedback**  
HDCPSet1 on

### HDCPSet2

Set the HDCP reporting mode of the **HDMI IN 2** port and performs the same type of function as the **HDCPSet1** command. on = enables HDCP detection; off = disables HDCP detection; sta = displays the current HDCPSet2 setting.

#### Syntax

```
HDCPSet2 X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

```
HDCPSet2 off
```

#### Feedback

```
HDCPSet2 off
```

### HDMIAUD

Enables / disables audio on the HDMI output. on = enables HDMI audio output; off = disables HDMI audio output; sta = displays the current HDMIAUD setting.

#### Syntax

```
HDMIAUD
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

```
HDMIAUD off
```

#### Feedback

```
HDMIAUD off
```

### Help

Displays the list of available commands. To obtain help on a specific command, enter the **Help** command followed by the name of the command.

#### Syntax

```
Help X
```

Parameter	Description	Range
X	Command name	Optional

#### Example

```
Help
```

#### Feedback

```
Command List
```

```
-----
```

```
Help
```

```
IPCFG
```

```
...
```

```
CliIPAddr
```

```
CliPort
```

## HUE

Sets the picture hue. Use the sta argument to display the current HUE value.

### Syntax

```
HUE X
```

Parameter	Description	Range
X	Value	0 ... 100, sta

### Example

```
HUE 40
```

### Feedback

```
HUE 40
```

## HZoom

Set the horizontal zoom for the output image. Use the sta argument to display the current HZoom value.

### Syntax

```
HZoom X
```

Parameter	Description	Range
X	Value	0 ... 50, sta

### Example

```
HZoom 10
```

### Feedback

```
HZoom 10
```

## INFOOSD

Enables / disables the OSD info screen. on = info screen always on, off = info screen is off, auto = info screen is displayed when a resolution change is made, then is automatically hidden, sta = displays the current INFOOSD setting.

### Syntax

```
INFOOSD X
```

Parameter	Description	Range
X	Value	on, off, sta

### Example

```
INFOOSD on
```

### Feedback

```
INFOOSD on
```



## INFOTMR

Sets the time interval (in seconds) of the info screen, before it is hidden. Use the sta argument to display the current INFOTMR value.

### Syntax

```
INFOTMR X
```

Parameter	Description	Range
X	Time interval	5 ... 100, sta

**Example**  
INFOTMR 60

**Feedback**  
INFOTMR 60

## Input

Sets the active input. Use the sta argument to display the currently active input.

### Syntax

```
Input X
```

Parameter	Description	Range
X	Input	HDMI 1, HDMI 2, VGA, sta

**Example**  
Input HDMI 2

**Feedback**  
Input HDMI 2

## IPAddUser

Adds a user for Telnet control. This command performs the same function as adding a user within the **Config** page of the web GUI. Refer to Config Menu in the AT-HD-SC-500 User Manual for more information.

### Syntax

```
IPAddUser X Y
```

Parameter	Description	Range
X	User name	20 characters (max)
Y	Password	20 characters (max)

**Example**  
IPAddUser BigBoss b055man

**Feedback**  
IPAddUser BigBoss b055man  
TCP/IP user was added

## IPCFG

Displays the current network settings for the AT-HD-SC-500.

### Syntax

```
IPCFG
```

This command does not require any parameters

### Example

```
IPCFG
```

### Feedback

```
IP Addr : 192.168.1.38
Netmask : 255.255.255.0
Gateway : 192.168.1.1
Telnet Port: 23
Http Port: 80
```

## IPDelUser

Deletes the specified TCP/IP user. This command performs the same function as removing a user within the **Config** page of the web GUI. Refer to the Config Menu in the AT-HD-SC-500 User Manual for more information.

### Syntax

```
IPDelUser X
```

Parameter	Description	Range
X	User	User name

### Example

```
IPDelUser BigBoss
```

### Feedback

```
IPDelUser BigBoss
TCP/IP user was deleted
```

## IPDHCP

Enables / disables DHCP mode on the AT-HD-SC-500. on = enables DHCP mode; off = disables DHCP mode; sta = displays the current IPDHCP setting. If this feature is disabled, then a static IP address must be specified for the AT-HDR-M2C. Refer to the [IPStatic](#) command for more information.

### Syntax

```
IPDHCP X
```

Parameter	Description	Range
X	Value	on, off, sta

### Example

```
IPDHCP on
```

### Feedback

```
IPDHCP on
```

## IPLogin

Enables / disables the use of login credentials when starting a Telnet session on the AT-HD-SC-500. If this feature is set to on, then the AT-HD-SC-500 will prompt for both the username and password. Use the same credentials as the web GUI. on = login credentials required; off = no login required; sta = displays the current IPLogin setting.

### Syntax

```
IPLogin X
```

Parameter	Description	Range
X	Value	on, off, sta

### Example

```
IPLogin off
```

### Feedback

```
IPLogin off
```

## IPPort

Sets the Telnet listening port for the AT-HD-SC-500. Use the sta argument to display the current port setting.

### Syntax

```
IPPort X
```

Parameter	Description	Range
X	Port	0 ... 65535, sta

### Example

```
IPPort 23
```

### Feedback

```
IPPort 23
```

## IPQuit

Terminates the Telnet session.

### Syntax

```
IPQuit X
```

**This command does not require any parameters**

### Example

```
IPQuit
```

### Feedback

```
IPQuit
```

### IPStatic

Sets the static IP address, subnet mask, and gateway (router) address of the AT-HDR-M2C. Before using this command, DHCP must be disabled on the AT-HDR-M2C. Refer to the **IPDHCP** command for more information. Each argument must be entered in dot-decimal notation and separated by a space. The default static IP address is 192.168.1.254.

#### Syntax

```
IPStatic X Y Z
```

Parameter	Description	Range
X	IP address	0 ... 255 (per byte)
Y	Subnet mask	0 ... 255 (per byte)
Z	Gateway (router)	0 ... 255 (per byte)

#### Example

```
IPStatic 192.168.1.112 255.255.255.0 192.168.1.1
```

#### Feedback

```
IPStatic 192.168.1.112 255.255.255.0 192.168.1.1
```

### IPTimeout

Specifies the time interval of inactivity before the Telnet session is automatically closed.

#### Syntax

```
IPTimeout X
```

Parameter	Description	Range
X	Interval (in seconds)	0 ... 60000

#### Example

```
IPTimeout 300
```

#### Feedback

```
IPTimeout 300
```

### LampCool

Sets the cool-down interval, in seconds, before the projector can be powered-off. During this time interval, the projector will not accept any commands until the "power off" command has been processed and the projector lamp has completed the cool-down cycle. Use the sta argument to display the current port setting.

#### Syntax

```
LampCool X
```

Parameter	Description	Range
X	Interval (in seconds)	0 ... 300, sta

#### Example

```
LampCool 120
```

#### Feedback

```
LampCool 120
```

## Lock

Locks the buttons on the front panel. This function is useful to prevent accidental activation of the front-panel buttons in a busy environment. Use the **Unlock** command to unlock the button on the front panel.

### Syntax

```
Lock
```

**This command does not require any parameters**

### Example

```
Lock
```

### Feedback

```
Lock
```

## LRAUD

Enables / disables the L/R audio output. on = enables L/R audio out, off = disables L/R audio out, sta = displays the current LRAUD setting.

### Syntax

```
LRAUD X
```

Parameter	Description	Range
X	Value	on, off, sta

### Example

```
LRAUD off
```

### Feedback

```
LRAUD off
```

## MENUTMR

Sets the time interval before the OSD menu system is automatically hidden after no activity. Use the sta argument to display the current MENUTMR setting.

### Syntax

```
MENUTMR X
```

Parameter	Description	Range
X	Interval (in seconds)	5 ... 100, sta

### Example

```
MENUTMR 60
```

### Feedback

```
MENUTMR 60
```

### MirrorV

Vertically mirrors the video. on = enables vertical mirroring, off = disables vertical mirroring, sta = displays the current MirrorV setting.

#### Syntax

```
MirrorV
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

```
MirrorV on
```

#### Feedback

```
MirrorV on
```

### Mreset

Resets the AT-HD-SC-500 to factory-default settings.

#### Syntax

```
MReset
```

**This command does not require any parameters**

#### Example

```
Mreset
```

#### Feedback

```
Mreset
```

### OSD

Sets the location of the OSD menu on the screen. 0 = Left-Top, 1 = Right-Top, 2 = Right-Bottom, 3 = Left-Bottom, 4 = Center, sta = displays the current OSD setting.

#### Syntax

```
OSD X
```

Parameter	Description	Range
X	Position	0 ... 4, sta

#### Example

```
OSD 2
```

#### Feedback

```
OSD 2
```

## OSDAAlpha

Sets the transparency of the OSD menu. Use the sta argument to display the current OSDAlpha setting.

### Syntax

```
OSDAAlpha X
```

Parameter	Description	Range
X	Opacity	0 ... 15, sta

**Example**  
OSDAAlpha 2

**Feedback**  
OSDAAlpha 2

## OSDBGRND

Sets the background color of the OSD menu. 0 = grey, 1 = cyan, 2 = magenta, 3 = yellow, sta = displays the current OSDBGRND setting.

### Syntax

```
OSDBGRND X
```

Parameter	Description	Range
X	Color	0 ... 3, sta

**Example**  
OSDBGRND 2

**Feedback**  
OSDBGRND 2

## PicReset

Resets all picture settings.

### Syntax

```
PicReset
```

**This command does not require any parameters**

**Example**  
PicReset

**Feedback**  
PicReset

## PTIMGHDMI

Sets the preferred HDMI input timing. This setting is applied to both **HDMI IN 1** and **HDMI IN 2** ports. Use the sta argument to display the current PTIMGHDMI setting.

### Syntax

```
PicReset
```

Parameter	Description	Range
X	Timing	0 ... 7, sta

### Preferred Timing List

0 = 800 x 600

1 = 1024 x 768

2 = 1280 x 720

3 = 1280 x 800

4 = 1366 x 768

5 = 1680 x 1050

6 = 1920 x 1080

7 = 1920 x 1200

## PTIMGVGA

Sets the preferred VGA input timing. Use the sta argument to display the current PTIMGVGA setting.

### Syntax

```
PTIMGVGA X
```

Parameter	Description	Range
X	Timing	0 ... 7, sta

### Example

```
PTIMGVGA 3
```

### Feedback

```
PTIMGVGA 3
```

## PWLock

Locks / unlocks the **DISPLAY** key on the front panel. on = enables DISPLAY lock, off = disables DISPLAY lock button, sta = displays the current PWLock setting.

### Syntax

```
PWLock
```

Parameter	Description	Range
X	Value	on, off, sta

### Example

```
PWLock on
```

### Feedback

```
PWLock on
```



## QOSD

Exits the OSD menu.

### Syntax

```
QOSD
```

This command does not require any parameters

### Example

```
QOSD
```

### Feedback

```
QOSD
```

## RAtIMac

Displays the MAC address of the AT-HDR-M2C.

### Syntax

```
RAtIMac
```

This command does not require any parameters

### Example

```
RAtIMac
```

### Feedback

```
b8-98-b0-01-21-7c
```

## SATRT

Sets the picture color saturation value. Use the sta argument to display the current SATRT setting.

### Syntax

```
SATRT X
```

Parameter	Description	Range
X	Saturation	0 ... 100, sta

### Example

```
SATRT 50
```

### Feedback

```
SATRT 50
```

## Select

Confirms the current selection in the OSD. Use the **Up** and **Down** commands to select (highlight) the desired option within the OSD.

### Syntax

```
Select
```

This command does not require any parameters

### Example

```
Select
```

### Feedback

```
Select
```

## SetCmd

Assigns an RS-232 or IP command to the specified button on the front panel.

### Syntax

```
SetCmd X[Y]
```

Parameter	Description	Range
X	Button	on, off, vol+, vol-, mute
Y	Command	Command string

### Example

```
SetCmd mute[Select]
```

### Feedback

```
SetCmd mute[Select]
```

## SetCmdFB

Sets the feedback string for the specified command key.

### Syntax

```
SetCmdFB X
```

Parameter	Description	Range
X	Feedback string	Feedback string

### Example

```
SetCmdFB mute[Selected]
```

### Feedback

```
SetCmdFB mute[Selected]
```

### SetCS

Sets the output color space. 0 = RGB, 1 = YUV, sta = displays the current SetCS setting.

#### Syntax

```
SetCS
```

Parameter	Description	Range
X	Color space	0, 1, sta

#### Example

```
SetCS 0
```

#### Feedback

```
SetCS 0
```

### SetEnd

Sets the end-character of the specified command.

#### Syntax

```
SetEnd X[Y]
```

Parameter	Description	Range
X	Command	on, off, vol+, vol-, mute, fbkon, fbkoff, fbkmute
Y	EOL character	None, CR, LF, CR-LF, Space, STX, ETX, null

#### Example

```
SetEnd off[CR-LF]
```

#### Feedback

```
SetEnd off[CR-LF]
```

### SetOff

Sets the time period (in seconds) to place the unit in standby. Use the sta argument to display the current SetOff setting.

#### Syntax

```
SetOff X
```

Parameter	Description	Range
X	Time interval	5 ... 240, sta

#### Example

```
SetOff 60
```

#### Feedback

```
SetOff 60
```

## SHARP

Sets the picture sharpness.

### Syntax

```
SHARP X
```

Parameter	Description	Range
X	Sharpness	0 ... 100, sta

**Example**  
SHARP 70

**Feedback**  
SHARP 70

## System

Displays system information about the AT-HD-SC-500. The sta argument must be specified.

### Syntax

```
System X
```

Parameter	Description	Range
X	Status	sta

**Example**  
System sta

**Feedback**  
 Model: AT-HD-SC-500  
 MAC Addr: b8-98-b0-01-21-7c  
 Address Type: DHCP  
 Netmask: 255.255.255.0  
 Gateway: 10.0.1.1  
 HTTP Port: 80  
 Telnet Port: 23  
 Firmware: 1.3.10  
 On/Up Time(dd HH:mm:ss): 0 4:57:29  
 Power Status: PWON

### Treble

Increases / decreases the amount of treble. In addition to specifying an integer value, the + and - arguments can be used, by themselves, to increase or decrease the amount of treble by 1 value, respectively. To display the current value, use the sta argument.

#### Syntax

```
TREBLE1 X
```

Parameter	Description	Range
X	Value	-12 ... 15, sta

#### Example

Treble 7  
Treble -

#### Feedback

Treble 7  
Treble 6

### TrigCEC

Triggers the stored CEC command.

#### Syntax

```
TrigCEC X
```

Parameter	Description	Range
X	Value	on, off, vol+, vol-, mute

#### Example

TrigCEC on

#### Feedback

TrigCEC on

### TrigIP

Trigger the stored IP commands to the Telnet client.

#### Syntax

```
TrigIP X
```

Parameter	Description	Range
X	Value	on, off, vol+, vol-, mute

#### Example

TrigIP vol+

#### Feedback

TrigIP vol+

## TrigRS

Triggers the stored commands from RS-232 or IP.

### Syntax

```
TrigRS X
```

Parameter	Description	Range
X	Value	on, off, vol+, vol-, mute

### Example

TrigRS mute

### Feedback

TrigRS mute

## UARTPara

Sets the baud rate, data bits, parity, and stop bits for the serial port. Each argument must be separated by a comma with no spaces.

### Syntax

```
UARTPara X
```

Parameter	Description	Range
W	Baud rate	2400, 4800, 9600, 19200, 38400, 57600, 115200
X	Data bits	7, 8
Y	Parity bit	0, 1, 2 (None, Odd, Even)
Z	Stop bits	1, 2

### Example

UARTPara 115200,8,0,1

### Feedback

UARTPara setting ok!

## Unlock

Unlocks the buttons on the front panel. Use the **Lock** command to lock the buttons on the front panel.

### Syntax

```
Unlock
```

**This command does not require any parameters**

### Example

Unlock

### Feedback

Unlock

## Up

Scrolls up the cursor, in the OSD menu, one position.

### Syntax

```
Up
```

This command does not require any parameters

### Example

```
Up
```

### Feedback

```
Up
```

## Version

Displays the current firmware version of the AT-HD-SC-500.

### Syntax

```
Version
```

This command does not require any parameters

### Example

```
Version
```

### Feedback

```
1.3.10
```

## VGAAuto

Executes the VGA auto-adjust. This command automatically adjusts the phase and clock of the VGA signal. A VGA display must be connected to the AT-HD-SC-500 when executing this command. Otherwise, the command will fail.

### Syntax

```
VGAAuto
```

This command does not require any parameters

### Example

```
VGAAuto
```

### Feedback

```
VGAAuto
```

## VidOutRes

Sets the video output resolution. Use the sta argument to display the current video output resolution.

### Syntax

```
VidOutRes
```

Parameter	Description	Range
X	Value	0 ... 27, sta

### Output Resolution List

0 = 800x600p60	14 = 1280x720p59
1 = 1024x768p60	15 = 1280x720p60
2 = 1280x800p60	16 = 1920x1080i50
3 = 1280x1024p60	17 = 1920x1080i59
4 = 1366x768p60	18 = 1920x1080i60
5 = 1400x1050p60	19 = 1920x1080p23
6 = 1600x900p60	20 = 1920x1080p24
7 = 1600x1200p60	21 = 1920x1080p25
8 = 1680x1050p60	22 = 1920x1080p29
9 = 1920x1200pRB	23 = 1920x1080p30
10 = 1280x720p25	24 = 1920x1080p50
11 = 1280x720p29	25 = 1920x1080p59
12 = 1280x720p30	26 = 1920x1080p60
13 = 1280x720p50	27 = NATIVE

### Example

```
VidOutRes 26
```

### Feedback

```
VidOutRes 26
```

## VOUT1

Increases / decreases the audio output volume. In addition to specifying an integer value, the + and - arguments can be used, by themselves, to increase or decrease the volume by 1 value, respectively. To display the current value, execute the VOUT1 command without any arguments.

### Syntax

```
VOUT1
```

Parameter	Description	Range
X	Value	-80 ... 6

### Example

```
VOUT1 4  
VOUT1 +
```

### Feedback

```
VOUT1 4  
VOUT1 5
```



### VOUtmute1

Mutes / unmutes the audio. on = enables muting; off = disables muting; sta = displays the current VOUtmute1 setting.

#### Syntax

```
VOUtmute1 X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

VOUtmute1 on

#### Feedback

VOUtmute1 on

### VOUtoSD

Enables / disables the volume bar in the OSD. on = displays volume bar; off = hides volume bar; sta = displays the current VOUtoSD setting.

#### Syntax

```
VOUtoSD X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

VOUtoSD on

#### Feedback

VOUtoSD off

### VZoom

Adjusts the vertical zoom (overscan) of the output image. Use the sta argument to display the current VZoom setting.

#### Syntax

```
VZoom X
```

Parameter	Description	Range
X	Value	0 ... 50, sta

#### Example

VZoom 10

#### Feedback

VZoom 10

### x1\$

Enables / disables the HDMI video output. on = enables HDMI output, off = disables HDMI output, sta = displays the current x1\$ setting.

#### Syntax

```
x1$ X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

x1\$ off

#### Feedback

x1\$ off

### Zoom

Enables / disables overscan. on = enables overscan; off = disables overscan; sta = displays the current Zoom setting.

#### Syntax

```
Zoom X
```

Parameter	Description	Range
X	Value	on, off, sta

#### Example

Zoom on

#### Feedback

Zoom off

