

# Firmware Update ~ AT-UHD-H2H-88M

The H2H matrices can be updated through webGUI only.


Needed items:

- New firmware - Downloaded from either atlona.com or through a box.com link sent by a Technical Support representative
- IP address of the Matrix
- Computer on the same network as the Matrix
- Username and password to access the webGUI of the Matrix

## Updating

- Plug a LAN cable into the matrix and your network router (if not already connected to the network)
- Type the IP address of the matrix into a web browser (as seen below)

**Note:** Computer must be on the same network as the Matrix to access through IP



**Important:** If any stability issues are experienced, disable any anti-virus or firewall that may be interfering with network communication to the Matrix. Once set up is done and the matrix GUI is no longer being used, the firewall and anti-virus can be re-enabled.



**Admin Login**

User name

root

Password

.....

Login


clear

A login screen will appear (this is the same log in for admin and general users).

- Login using the username and password (this would have been set up during installation)

Once logged in:

- Select the link named 'Firmware' on the left side menu



The screenshot shows the ATLONA web interface. At the top, the ATLONA logo and tagline "Connecting Technology" are on the left, and technical support information is in the center. The model number "AT-UHD-H2H-88M" is on the right. A left sidebar contains a "Home" section with links to "Status" and "Firmware", a "Settings" section with links to "Network", "Control", and "Users", and a "Configuration" section with links to "I/O", "Route Memory", "EDID", "HDCP", and "Logout". The main content area has a "Firmware Status" section with a table showing UI Firmware (1.4.28) and HDMI (1.4.25). Below this is a message to "Check for the most recent firmware update!". The "Firmware Update" section includes a "Matrix" label, a "File" input field with a "Browse..." button, the text "No file selected.", and an "Update" button.

Matrix	
UI Firmware	1.4.28
HDMI	1.4.25

Check for the most recent **firmware update!**

**Firmware Update**

Matrix

File  No file selected.

The firmware page displays the matrix UI and HDMI firmware versions to make it easier to see what needs to be updated.

- Select the browse button under Matrix in the Firmware Update section
- Select the new firmware file that was downloaded either from [atlona.com](http://atlona.com) or [box.com](http://box.com)
- Press the update button

A progress bar will display as the update is completed. After the update is complete, if a restart is required, the WebGUI will display a prompt. The firmware update is now complete and the matrix is ready to be used.